

<b>SANYO</b>	No.3707	<b>2SA1769/2SC4613</b>
		PNP/NPN Epitaxial Planar Silicon Transistors <b>160V/700mA Switching Applications</b>

**Applications**

- Color TV audio output, converter, inverter.

**Features**

- Adoption of MBIT processes.
- High breakdown voltage and large current capacity.
- Fast switching speed.

( ) : 2SA1769

**Absolute Maximum Ratings at Ta = 25°C**

			unit
Collector-to-Base Voltage	V <sub>CB0</sub>	(-)	180 V
Collector-to-Emitter Voltage	V <sub>CE0</sub>	(-)	160 V
Emitter-to-Base Voltage	V <sub>EBO</sub>	(-)	6 V
Collector Current	I <sub>C</sub>	(-)	0.7 A
Collector Current (Pulse)	I <sub>CP</sub>	(-)	1.5 A
Collector Dissipation	P <sub>C</sub>		1.5 W
			10 W
Junction Temperature	T <sub>j</sub>		150 °C
Storage Temperature	T <sub>stg</sub>		-55 to +150 °C

T<sub>c</sub> = 25°C

**Electrical Characteristics at Ta = 25°C**


			min	typ	max	unit
Collector Cutoff Current	I <sub>CB0</sub>	V <sub>CB</sub> = (-)120V, I <sub>E</sub> = 0			(-)	0.1 μA
Emitter Cutoff Current	I <sub>EBO</sub>	V <sub>CE</sub> = (-)4V, I <sub>C</sub> = 0			(-)	0.1 μA
DC Current Gain	h <sub>FE</sub> (1)	V <sub>CE</sub> = (-)5V, I <sub>C</sub> = (-)100mA	100*		400*	
	h <sub>FE</sub> (2)	V <sub>CE</sub> = (-)5V, I <sub>C</sub> = (-)10mA	90			
Gain-Bandwidth Product	f <sub>T</sub>	V <sub>CE</sub> = (-)10V, I <sub>C</sub> = (-)50mA		120		MHz
C-E Saturation Voltage	V <sub>CE(sat)</sub>	I <sub>C</sub> = (-)250mA, I <sub>B</sub> = (-)25mA		0.12	0.4	V
				(-0.2)	(-0.5)	
B-E Saturation Voltage	V <sub>BE(sat)</sub>	I <sub>C</sub> = (-)250mA, I <sub>B</sub> = (-)25mA	(-)	0.85	(-)	1.2 V
C-B Breakdown Voltage	V <sub>(BR)CBO</sub>	I <sub>C</sub> = (-)10μA, I <sub>E</sub> = 0	(-)	180		V
C-E Breakdown Voltage	V <sub>(BR)CEO</sub>	I <sub>C</sub> = (-)1mA, R <sub>BE</sub> = ∞	(-)	160		V
E-B Breakdown Voltage	V <sub>(BR)EBO</sub>	I <sub>E</sub> = (-)10μA, I <sub>C</sub> = 0	(-)	6		V

\* : The 2SA1769/2SC4613 are classified by 100mA h<sub>FE</sub> as follows.

Continued on next page.

100 R 200	140 S 280	200 T 400
-----------	-----------	-----------

**Switching Time Test Circuit**




2Q<sub>IB1</sub> = -20I<sub>B2</sub> = I<sub>C</sub> = 300mA  
(For PNP, the polarity is reversed).

Unit (Resistance : Ω, Capacitance : F)

**Package Dimensions 2042A**

(unit : mm)









SANYO: TO126ML









2SA1769/2SC4613

Continued from preceding page.





			min	typ	max	unit
Output Capacitance	$C_{ob}$	$V_{CB} = (-)10V, f = 1MHz$		8		pF
Turn-ON Time	$t_{on}$	See specified Test Circuit.		(11)		pF
Storage Time	$t_{stg}$	◇		50		ns
Fall Time	$t_f$	◇		(60)		ns
				1000		ns
				(900)		ns
				60		ns
				(60)		ns



2SA1769/2SC4613



# 2SA1769/2SC4613



■ No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.

■ Anyone purchasing any products described or contained herein for an above-mentioned use shall:

- ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use.
- ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.

■ Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.